

FUJI ELECTRIC FUZZY LOGIC CONTROLLERS ARE THE LEADERS IN PRECISION CONTROL

Breakthrough technology. That's what the Fuji PX series fuzzy logic controllers are all about. Faster. Smarter. Tougher.

More Versatile. More Features. Redesigned from the ground up. Redeveloped from the inside out. Welcome to the 21st century, and meet the leaders in control technology.

The NEMA 4X protection makes them tough enough to withstand the harshest of environments. Fuji's fuzzy logic algorithm makes them smart enough to learn your process and make rapid, accurate adjustments. A variety of choices for number of buttons, DIN size, configuration, and options make them versatile enough to match your individual needs.

All of the PX controllers employ Fuji's patented fuzzy logic algorithm with PID Autotune. These controllers "learn" your process, using the PID parameters as a starting point for all decisions made by the controller. This intelligence allows your process to reach its setpoint in the shortest time possible while virtually eliminating overshoot. The end result is that your process maintains a steady setpoint.

Eight-segment ramp/soak programming. Advanced security options. Versatile programming. Fuzzy logic intelligence. NEMA 4X protection. All of these features come STANDARD in a PX controller.



FEATURES

- **Choose Among 1/4 DIN, 1/8 DIN, 72mm, and 1/16 DIN Sizes**

There's a size available to accommodate your space needs

- **Front Panel Key Choices**

Choose between eight-button or three-button operation

- **Fuzzy Logic Control with PID Autotune**

The controller uses artificial intelligence to learn your process

- **NEMA 4X Protection**

It's tough enough for the harshest of environments

- **All Parameters Are Display Maskable**

Hide unused parameters

- **8-Segment Ramp/Soak Programming is a Standard Feature**

Set four setpoints, four ramp rates, and four soak periods

- **Program Loader Interface**

Download programs from your PC

- **Wide Input Selection**

A variety of choices for your input needs

- **Low-Voltage Power Supply Option**

24V AC/DC option

- **Lower Prices than Other PID Controllers**

You get more standard features for less money

- **Three-Year Warranty**

Protects against manufacturing defects

PX SERIES, CONTINUED

PX SERIES SPECIFICATIONS

GENERAL SPECIFICATIONS

RATED VOLTAGE	85 to 264 VAC or 24V AC/DC $\pm 10\%$
POWER CONSUMPTION	10VA or less (100 VAC), 15VA or less (240 VAC)

INPUT SIGNAL

INPUT SIGNAL	Thermocouples: J, K, R, B, S, T, E, N and PL2 RTDs: Pt100 DC Voltage/Current: 1 to 5 VDC, 0 to 5 VDC, 4 to 20mA DC, and 0 to 20mA DC
INPUT FILTER	0 to 900.0 sec, setting in 0.1 sec steps

CONTROL FUNCTION

CONTROL ACTION	PID control with auto-tuning; Fuzzy control with auto-tuning
PROPORTIONAL BAND (P)	0 to 999.9% of full scale (FS), setting in 0.1% steps
INTEGRAL TIME (I)	0 to 3200 seconds, setting in 1 second steps
DIFFERENTIAL TIME (D)	0 to 999.9 seconds, setting in 0.1 second steps
PROPORTIONAL CYCLE	1 to 150 seconds, setting in 1 second steps
HYSTERESIS WIDTH	0 to 50% FS, setting in 1 E.U. steps, On/Off action only
INPUT SAMPLING CYCLE	0.5 seconds

OUTPUT

STANDARD OUTPUT TYPE	One of the following control output types is selected: 1. Relay Contact (SPDT): 220 VAC/30 VDC, 3A (resistive load) 2. SSR/SSC Drive (voltage pulse): 15 to 30 VDC at ON/0.5 VDC or less at OFF, Current 60mA or less 3. 4 to 20mA DC: Allowable load resistance: 600 Ω or less 4. 0 to 10 VDC: Allowable load resistance: 500k Ω or more 5. Triac: 1A, 250 VAC
DUAL-OUTPUT TYPE (HEAT/COOL)	For dual output type, one of the following five control output types is selected on both heating and cooling types (not available on PXW/Z-4 type) 1. Relay Contact SPDT 220 VAC/30 VDC, 3A (resistive load) 2. SSR/SSC Drive (Voltage Pulse). ON: 15 to 30 VDC. OFF: 0.5 VDC or less. Current: 60mA or less 3. 4 to 20mA DC: Allowable load resistance: 600 Ω or less 4. 0 to 10 VDC: Allowable load resistance: 500k Ω or more 5. Triac: 1A, 250 VAC

OPERATION AND DISPLAY SECTION

PARAMETER SETTING METHOD	PXW: Digital setting with 3 keys PXZ: Digital setting with 8 keys
PV/SV DISPLAY METHOD	PXZ-4: PV/SV Red LED display, 4-digit PXW, PXZ-5, 7, 9: Dual PV/SV LED display, 4 digits each, PV= Red, SV=Green
STATUS DISPLAY	Control output, alarm output, heater burnout alarm output
INDICATION ACCURACY (at 23°C)	Thermocouple: $\pm 0.5\%$ FS ± 1 digit $\pm 1^\circ\text{C}$ R Thermocouple: 0 to 400°C; $\pm 1\%$ FS ± 1 digit $\pm 1^\circ\text{C}$ B Thermocouple: 0 to 500°C; $\pm 5\%$ FS ± 1 digit $\pm 1^\circ\text{C}$ RTD, Voltage, Current: $\pm 0.5\%$ FS ± 1 digit

ALARM

ALARM OUTPUT	Relay contact (SPST), 220 VAC/30 VDC, 1A (resistive load) PXW/Z-4 type: 1 point; Other types: 2 points (Configurable as absolute, deviation, zone, or combination alarms with or without the hold features)
HEATER BURNOUT ALARM OUTPUT	Relay contact (SPST), 220 VAC/30 VDC, 1A (resistive load), PXW/Z-4 type: not available

FUNCTIONS

PARAMETER MASK FUNCTION	Parameter display is disabled by software
RAMP/SOAK FUNCTION	4-ramp/4-soak

STRUCTURE

MOUNTING METHOD	Panel mounting or surface mounting. Surface mounting: PXW/Z-4 type only
EXTERNAL TERMINAL	PXW/Z-4 Type: 8-pin or 11-pin socket. Other Types: Screw terminal (M3.5 screw)
DIMENSIONS (WxHxD)	PXW/Z-4: 1/16 DIN 1.89 x 1.89 x 3.37 in (48 x 48 x 85.7mm) PXW/Z-5: 1/8 DIN 2.07 x 3.96 x 3.77 in (52.5 x 100.5 x 95.8mm) PXW/Z-7: 7/2 mm 3.01 x 3.01 x 3.77 in (76.5 x 76.5 x 95.8mm) PXW/Z-9: 1/4 DIN 3.96 x 3.96 x 3.77 in (100.5 x 100.5 x 95.8mm)
PROTECTIVE STRUCTURE	Front Panel: NEMA 4X (equivalent to IEC standards IP66); protection against corrosion, windblown dust and rain, and hose directed water Rear Case: IEC IP20; protection against solid object up to 12 mm
INSTALLATION CATEGORY	Category II
POLLUTION DEGREE	2
UL FILE NO.	E131280S

PX SERIES, CONTINUED

PX SERIES ORDERING INFORMATION

P **X** **A** **B** - **C** **D** **E** **2** - **F** **V** - **G**

To create a part number fill in the boxes above with the appropriate number and/or letter from the corresponding box below.

Box A: Model

W = 3-Button keypad* N/C
Z = 8-Button keypad N/C

* Same price for all models except 1/16 DIN

Box B: Front panel size

4 = 1/16 DIN* \$ 179
5 = 1/8 DIN 270
7 = 72mm 300
9 = 1/4 DIN 315

* Mounting socket required. See Accessories below

Box C: Kinds of Input

T = Thermocouple °C N/C
R = Thermocouple °F N/C
N = RTD (Pt100) °C N/C
S = RTD (Pt100) °F N/C
B = 4-20mA DC, 1-5 VDC N/C
A = 0-20mA DC, 0-5 VDC N/C

Box D: Control Output 1

A = Relay contact (reverse action) N/C
B = Relay contact (direct action) N/C
C = SSR/SSC driver (reverse action) N/C
D = SSR/SSC driver (direct action) N/C
E = 4-20mA DC (reverse action) N/C
F = 4-20mA DC (direct action) N/C
G = Triac 1A, 250 VAC (reverse action)* N/C
H = Triac 1A, 250 VAC (direct action)* N/C
P = 0-10 VDC (reverse action)* N/C
Q = 0-10 VDC (direct action)* N/C

* No agency approvals available for this option

Box E: Control Output 2*

Y = None N/C
A = Relay contact (reverse action) \$ 55
B = Relay contact (direct action) 55
C = SSR/SSC driver (reverse action) 55
D = SSR/SSC driver (direct action) 55
E = 4-20mA DC (reverse action) 55
F = 4-20mA DC (direct action) 55
G = Triac 1A, 250 VAC (reverse action)** 55
H = Triac 1A, 250 VAC (direct action)** 55
P = 0-10 VDC (reverse action)** 55
Q = 0-10 VDC (direct action)** 55

* Not available on PXZ4

** No agency approvals available for this option

Box F: Alarm Options

2 = Heater break alarm* 50
3 = Process alarm & heater break alarm* 80
4 = None N/C
5 = Process alarm 30

* Heater break option requires current transformers.

See Accessories below.

Option not available on PXZ4, or with 4-20mA, 0-10V output

Box G: Power Supply Options

Blank = 85-264 VAC (standard, no code necessary) N/C
D = 24V AC/DC 30

PX SERIES ACCESSORIES

ATX1NS	Solder-Type 8-Pin Socket for PXW/Z-4 without H/L Alarm Option	\$ 10
PG-08	Screw-Down-Type 8-Pin Socket (terminals on back) for PXW/Z-4 without H/L Alarm Option	5
TP28S	Screw-Down-Type 8-Pin Socket (UL) (terminals on front) for PXW/Z-4 without H/L Alarm Option	10
PG-11	Screw-Down-Type 11-Pin Socket (terminals on back) for PXW/Z-4 with H/L Alarm Option	6
TP411SBA	Screw-Down-Type 11-Pin Socket (terminals on back) for PXW/Z-4 with H/L Alarm Option	12
CTL-6-S	Heater Break Current Sensing Transformer for heater current 0 to 30A	23
CTL-12	Heater Break Current Sensing Transformer for heater current 20 to 50A	40
PX LOADER ASSEMBLY	Program loader for PX series	170